



New generation intelligent Genset controller.

When you use it you will **experience** the difference!!!

GU621A Genset Controller

Description:

GU621A is an Automatic Mains (Utility) Failure module which is designed to monitor the mains (utility) and on failure automatically starts the generator and transfers the load. On return of the mains (utility) the controller automatically returns the load to the mains and stops the Generator after a cool down period.

The module also monitors and protects the engine, indicating operational status, fault conditions and metering on the front panel LCD and LED's.

- 128 x 64 graphic LCD
- True RMS measuring
- Configuration of parameters by front panel push buttons or communication software
- RS485, RS232, or USB port for remote communication.
- Configurable fuel output energise to stop or energise to run.
- 7 Configurable inputs.
- 5 Configurable outputs, 2 used for ATS control.
- 2 Analogue inputs configurable for different senders for Oil pressure and Engine temperature.
- 2 Aux.configurable analogue inputs
- Push Buttons for manual control of GCR/MCR

Technical Parameter:

Engine and Alternator Metering:

- Mains phase voltage L1-N L2-N L3-N
- Mains line voltage L1-L2 L2-L3 L3-L1
- Mains frequency Hz
- Generator phase voltage L1-N L2-N L3-N
- Generator line voltage L1-L2 L2-L3 L3-L1
- Generator current I1 I2 I3
- Generator frequency Hz
- Engine speed RPM
- Generator phase apparent power kVA A1 A2 A3 ΣA
- Generator phase active power kW P1 P2 P3 ΣP
- Generator phase reactive power kVar Q1 Q2 Q3 ΣQ
- Generator phase power factor PF PF1 PF2 PF3
- Generator total active power kwh
- Generator total reactive power kVarh
- Battery voltage Vdc
- Engine running hours counter h
- Engine temperature °C (°F)
- Oil pressure BAR (PSI)
- Aux. configurable analogue inputs #1
- Aux. configurable analogue inputs #2

Warning and Shutdown

Alarms:

- Low oil pressure
- High engine temperature
- Over/ under speed
- High/ low gen voltage
- High/ low Mains voltage
- Start failure
- Stop failure
- Emergency stop
- Charge failure
- High/low battery voltage
- Aux. shutdown alarm
- Aux. Warning
- Over current

Optional Function (on ordering):

- Speed control for DC actuator motor
- Operating Temperature -40 to 70°C.
- With GPRS-DTU or Ethernet-DTU for remote communication instead of Rs485, RS232, or USB port for remote communication.
- J1939 CAN bus communication port.

Specification:

- DC supply: 8.0V to 35V continuous
- Cranking drop outs: 0V for 100ms, assuming DC supply was at least 10V before dropout and recovers to 5V
- AC input voltage: phase voltage 15-300 Vac RMS (AC frequency ≥ 40 Hz)
- AC input frequency: 3-70Hz (voltage ≥ 15 V)
- Max operating current: @12V 0.4A, @24V 0.2A
- Max frequency input of the speed sender: 10000Hz
- Voltage input of the speed sender: 1-70 Vdc
- Accuracy $\pm 0.5\%$
- Start relay output: 16A/30Vdc
- Fuel relay output: 16A/30Vdc
- Aux. control relay output: 3 A/30Vdc
- Protection: Controller fascia IP65 when correctly installed
- Operating temperature: -20 to 70°C
- Storage temperature: -30 to 80°C


Harsen®




The control specialist of dynamical power

Outline Dimension Drawing:

Module Dimension	W 192mm x H 144mm
Panel cutout	W 174mm x H 126mm
Depth	D56mm (without connection)




Panel Cutout



Front View




Side View



Back View

Typical Wiring Diagram:



JNH Harsen International



Harsen International Ltd maintains a policy of continuous development and reserves the right to change the details shown on this data sheet without prior notice. The contents are intended for guidance only.
[Http://www.harseninternational.com](http://www.harseninternational.com)

HSJ1009100505GU621A

**Harsen
Product**

Professional

Innovation

Quality

Service

WWW.HARSENINTERNATIONAL.COM

Harsen®